



**Name:** CCTV keyboard controller  
**Model:** BSC02275

**Special Requirements:**

Weight: 1.4KG  
 Volume: 330\*174\*135MM

### Product Feature

The joystick of PTZ could control the turning of PTZ conveniently

The layout of the keyboard is so reasonable that make the operation simple and Easy to learn

It can complete all operation and programming of Ancend matrix switch control system.

It not only can control PTZ, lens and other equipments efficiently, but also control speed dome and decoder independently.

Control distance could achieve 1.5 kilometers after connecting EK-3050 master

keyboard with EK-2000/2200/2400 matrix switch control system by RS - 485 Interface

Control DVR: User can use keyboard to operate DVR

### Electrical Specification

Operating Voltage: DC9V

Rated Power: ≤5W

Control Interface: RS-485, With Baud rate: 2400bps/s, 4800bps/s, 9600bps/s, 19200bps/s

Protocol: ancend, Pelco-D, Pelco-P,

Connectors:RJ-45 to switcher/controller system via terminal block used for RS-485 And power  
Equipped with 9VDC regulated power source and terminal block

Architecture and surface: Deep gray plastic support board, aluminum alloy and Sandblast panel, and black button.

### **Environment**

Operating Temperature : -10 ~ 45°C

Storage Temperature : - 30 ~ 70°C

Humidity: Relative humidity 0%~95%(non-condensing)

Vibration:3g sine wave,15Hz~2000Hz

Shock:50g,11ms,1/2sine wave